

# Product data sheet FT 4 A Acoustic \*



SHEV button with acoustic signal for connection to GEZE SHEV control panels

## **AREAS OF APPLICATION**

- → For the connection to GEZE control panels
- → For manual smoke and heat extraction alarm triggering
- $\rightarrow$  Cable entry from above, below or the rear side

# FT 4 A Acoustic



### **PRODUCT FEATURES**

- → Robust, lockable die-cast aluminium housing
- → LED operating status displays Alarm, Window OPEN, Operation OK, fault
- ightarrow Acoustic signal in the event of alarm and fault can be activated via DIP switch
- → Reset button for resetting the alarm
- → Verifiable release by snapping of push button

### TECHNICAL DATA

Productname	FT 4 A Acoustic *

### **VARIANTS / ORDER INFO**

Designation	Description	ldent- No.	Colour	Dimensions	Operating voltage
SHEV button FT 4 A Acoustic, *	in aluminium housing with acoustic signal for alarm/fault, incl. label "SMOKE VENT"	198926	grey RAL 7035	126 x 126 x 32 mm	24 V DC
SHEV button FT 4 A Acoustic, *	in aluminium housing with acoustic signal for alarm/fault, incl. label "SMOKE VENT"	198925	orange RAL 2011	126 x 126 x 32 mm	24 V DC

**GEZE GmbH** Reinhold-Vöster-Straße 21–29 D-71229 Leonberg TEL +49 7152 203-0 WEB www.geze.de Mail info.de@geze.com 2024-04-07T03:19:03Z

<sup>\*</sup> The products designated above may vary in form, type, characteristics, function, or availability depending on the country. Please get in touch with your GEZE contact person if you have any questions.